


# **DOSSERT**®

## TYPE SX-A, SX-A-90

## **Stud Expansion Connector for Pipe**

## Both SX-A and SX-A-90 connect copper stud to aluminum bus.

An expansion stud connector for joining a tubular bus to a threaded or unthreaded, transformer or terminal, stud. The movements of the conductors caused by thermal expansion and contraction or settling foundations are efficiently absorbed by the flexible braided linkages. Type SX is furnished with an alignment guide for connections where axial alignment is required.



BOLTS, NUTS, FLAT

AND LOCK WASHERS

#### **Material**


Stud - Copper Alloy Bus - Aluminum Alloy


#### **Hardware**

See image

#### **Notes**

For a 90 degree stud connector add -90 to the Catalog Number. EX. For at 1"-T14 stud to 1in SPS connector with 90 degree stud connector order: SX100-100A-T14-90









### **Ordering Information**

CATALOG NUMBER	STUD DIAMETER	THREADS PER INCH	SPS	FIG. NO.	DIMENSIONS IN INCHES		BOLT SIZE	
					Α	В	STUD	PIPE
SX100-200A-T14	1	14	2	1	2 3/4	3 1/4	1/2	1/2
SX112-100A-T12	1 1/8	12	1	1	2	3 1/8	3/8	1/2
SX112-200A-T12	1 1/8	12	2	1	2 3/4	3 1/4	1/2	1/2
SX150-150A-T12	1 1/2	12	1 1/2	1	2 3/4	3 1/4	1/2	1/2
SX150-200A-T12	1 1/2	12	2	1	2 3/4	3 1/4	1/2	1/2
SX150-300A-T12	2	12	3	2	2 3/4	3 1/2	1/2	5/8
SX200-350A-T12	2	12	3 1/2	2	2 3/4	3 1/2	1/2	5/8
SX200-400A-T12	2	12	4	2	2 3/4	3 1/2	1/2	5/8
SX250-300A-T12	2 1/2	12	3	2	2	3 1/2	1/2	5/8